

# ECE 417 Multimedia Signal Processing

## Homework 1

UNIVERSITY OF ILLINOIS  
Department of Electrical and Computer Engineering

Assigned: Tuesday, 8/25/2020; Due: Monday, 8/31/2020  
Reading: [Strang, Section 6.1](#) and [Gallager, pp. 33-34, 36, 39-43, 45](#)

### Problem 1.1

Suppose that  $x[n]$  is the following time-shifted rectangle function:

$$x[n] = u[n - 15] - u[n - 31] \quad (1.1-1)$$

Find  $X(\omega)$ .

### Problem 1.2

Suppose that  $\vec{x} = [x_1, x_2]^T$  is a Gaussian random vector, with mean vector  $\vec{\mu}$  and covariance matrix  $\Sigma$  given by:

$$\vec{\mu} = \begin{bmatrix} 2 \\ 5 \end{bmatrix}, \quad \Sigma = \begin{bmatrix} 9 & 0 \\ 0 & 4 \end{bmatrix} \quad (1.2-1)$$

Remember that the standard normal CDF is defined to be:

$$\Phi(z) = \frac{1}{\sqrt{2\pi}} \int_{-\infty}^z e^{-\frac{1}{2}t^2} dt \quad (1.2-2)$$

In terms of  $\Phi(z)$ , find  $\Pr\{x_1 > 4\}$ , the probability of the event that  $x_1$  is greater than 4.

### Problem 1.3

Let  $A$  be a  $2 \times 2$  matrix, and let  $x$  be one of its elements. All of its other elements are known, and are given as:

$$A = \begin{bmatrix} x & 3 \\ -1 & 2 \end{bmatrix} \quad (1.3-1)$$

The eigenvalues of  $A$  are given by

$$\lambda = -\frac{b}{2} \pm \frac{\sqrt{b^2 - 4ac}}{2a} \quad (1.3-2)$$

for some particular values of  $a$ ,  $b$ , and  $c$ . Find  $a$ ,  $b$ , and  $c$ , in terms of  $x$ , such that Equation (1.3-2) gives the eigenvalues of  $A$ .

### Problem 1.4

Let  $A$  be a  $2 \times 2$  matrix, and let  $x$  be one of its elements. All of its other elements are known, and are given as:

$$A = \begin{bmatrix} x & 3 \\ -1 & 2 \end{bmatrix} \quad (1.4-1)$$

Suppose that you are given one of its eigenvalues,  $\lambda$ , and you want to find the corresponding eigenvector. As you know, the scale of an eigenvector is arbitrary, so let's arbitrarily set its first element to 1:  $\vec{v} = [1, v_2]^T$ . Solve for its second element,  $v_2$ , in terms of  $\lambda$ .